

**FS80**

FS80-CM0907D00W

- Rozlišení: 5–16 megapixelů
- Velikost pixelu: 3,2 μm
- Snímková frekvence: až 42 snímků za sekundu
- Integrované ostření a osvětlení
- Krytí IP: IP67

**POPIS PRODUKTU**

Pevný průmyslový snímač Zebra FS80 představuje špičkové řešení pro náročné aplikace sledování v logistice a výrobě, které vyžadují vysokou rychlost snímání, široké zorné pole a čtení na velkou vzdálenost. Je vybaven snímači s vysokým rozlišením, výkonným integrovaným osvětlením a je spravován pomocí intuitivní softwarové platformy Zebra Aurora Focus, která zjednodušuje nastavení, nasazení a provoz. Díky své robustní konstrukci (IP67), flexibilním možnostem připojení a sadě C-mount objektivů je FS80 navržen tak, aby optimalizoval produktivitu a nahradil několik standardních kamer, čímž snižuje náklady a složitost instalace.

Klíčové body:

- FS80 je navržen pro náročné sledovací a trasovací aplikace v logistice a výrobě.
- Díky snímačům s vysokým rozlišením a výkonnému osvětlení dokáže snímat rychle se pohybující kódy na velkou vzdálenost.
- Integrované multifunkční světlo (ZIML) je k dispozici v bílé, červené nebo infračervené variantě pro optimální čitelnost.
- Software Zebra Aurora Focus sjednocuje správu všech pevných průmyslových skenerů a zjednodušuje jejich nasazení.
- Odolné pouzdro s krytím IP67 a konektory M12 zajišťují spolehlivý provoz v náročných průmyslových podmínkách.
- Zařízení podporuje různé C-mount objektivy (8 mm až 35 mm) a doplňky jako polarizační filtry.
- Softwarové licence umožňují rozšíření funkcí, například pro rychlejší snímání nebo pokročilé OCR.
- Skener poskytuje vizuální i zvukovou zpětnou vazbu o stavu čtení, viditelnou i v hlučném prostředí.
- Podporuje širokou škálu komunikačních protokolů včetně TCP/IP, Ethernet/IP a PROFINET.
- Volitelný polarizační kryt zlepšuje čtení na reflexních površích nebo přes plastové fólie.

SPECIFIKACE

12408_Pixelsize	3.2 x 3.2 μm
12410_Frame rate Max	40
12413_Javascript support	Ano
12415_Certification - Environment	EN IEC 63000:2018
12416_Certification - Electricity	UL, CSA, IEC 61010
12417_Certification - EMC	EN 55011, EN 61326, FCC Part 15
12418_Dimensions (with lens cap)	75 x 120 x 75 mm

12419_Dimensions (without lens cap)	75 x 57 x 75 mm
12420_Weight (with lens cap)	504 g
12421_Weight (without lens cap)	407 g
Aktuální spotřeba	15 W (625 mA @ 24 VDC)
Focus	Manual iris
Interface out	One M12 X-Coded 1GbE, One M12-A 12-pin (female) Power & GPIO, One M12-A 12-pin (male) VGA
Lens Barrel	C-Mount
Materiál	Hliník
Rozlišení	9 MP
Size	75 x 120 x 75 mm
Software performance	Standard 2D Barcode Decoder
Storage	32 GB
Temperature range	0 °C till 45 °C
Type of lens	Fixed
Type of scanner	Fixed Scanner

Digital IO and Power Connector

The digital IO and power connector is an M12 12-pin female connector (M12-CBL-PWRIO-3) that transmits and receives digital I/O signals and provides power to your device.




Table: M12-CBL-PWRIO-3 Digital IO and Power Pin-Out Diagram

Pin Number	Wire Color	Function	Description
1	Brown	OUT_COMMON	Open-isolated industrial auxiliary signal (output) common. Ensure that OUT_COMMON is connected to the return path when using the F580 with the Multi-Feature Integrated Light.
2	Pink	NA	Not Supported
3	White	OUT2	Open-isolated industrial auxiliary signal 2 (output). Supported function: user-IO 2 (pin 2 of 3).
4	Green	+VDC	Positive pin of the power provided to your device. This pin must be connected to a +24 V (+/- 10% power supply).
5	Pink	IN3	Open-isolated industrial auxiliary signal 3 (input).
6	Yellow	IN_COMMON	Open-isolated industrial auxiliary signal (input) common. Supported function: Whether you should connect this pin to an electrical return path or a voltage source depends on whether the third-party device is sourcing or sinking the current.
7	Black	IN5	Open-isolated industrial auxiliary signal 5 (input).
8	Grey	IN6	W_ALARM
9	Red	IN4	Open-isolated industrial auxiliary signal 4 (input).
10	Violet	OUT3	Open-isolated industrial auxiliary signal 3 (output).
11	Grey/White	-VDC	Negative pin of the power provided to your Zebra F580. This pin must be connected to the electrical return path.
12	Red/Blue	OUT1	Open-isolated industrial auxiliary signal 1 (output). Supported function: user-IO 1 (pin 2 of 3).

Ethernet Connector

The Ethernet connector is an M12 (female) 8-pin X-coded connector that provides TCP/IP communication.





Table: Digital IO and Power Pin-Out Diagram

Pin Number	Signal Name	Description
1	MDI_1+	Bidirectional data A+
2	MDI_1-	Bidirectional data A-
3	MDI_2+	Bidirectional data B+
4	MDI_2-	Bidirectional data B-
5	MDI_4+	Bidirectional data D+
6	MDI_4-	Bidirectional data D-
7	MDI_3-	Bidirectional data C-
8	MDI_3+	Bidirectional data C+


Power and IO Y Cable

The Power and IO Y cable (CBL-PWRIO500-M1210) transmits and receives digital IO signals and provides power to the F580 (M12-A 12-pin Male) and the Multi-Feature Integrated Light (M12-A 8-pin Female).



Flying Leads Color (24 AWG)	Function	12 Pin A-Coded Male M12 to F580	8 Pin A-Coded Female M12 to MFL
Green	OUT_COMMON	1 Green	6 Green
Green	Green must be connected to VDC to operate the Multi-Feature Integrated Light.		
Brown	N/A	2 Brown	-
Yellow	OUT2	3 Yellow	-
Red	+VDC	4 Red	1 Red
Grey	IN3	5 Grey	-
White/Violet	IN_COMMON	6 White/Violet	-
Violet	IN5	7 Violet	-
White/Yellow	IN6	8 White/Yellow	-
White/Brown	IN4	9 White/Brown	-
Black	-VDC	10 Black	8 Black
Orange	FASS	-	7 White/Orange
Blue	FAIS	-	2 White/Blue
White/Green	RESERVED_PROG	-	3 White/Green

The digital I/O and power connector is an MPU I/O pin header connector (MPU I/O) that transmits and receives digital I/O signals and provides power to your device.




No.	Fit	Wiring	Technical Support	Recommendation
1	Green	OUT - COMMON	Open-terminal industrial auxiliary voltage (output) common.	
2			 Shows that OUT - COMMON is connected to the return path when using the FSR0 with the Multi-Feature Integrated Light.	
3	Pink	NA	Not supported	
4	White	OUT2	Open-terminal industrial auxiliary voltage 2 (output).	
			Supported function: see table 2 (output 2 of 3).	
5	Green	-VDC	Positive pole of the power provided to your device.	
			 This pin must be connected to a +24 V or +18V power supply.	
6	Pink	PE2	Open-terminal industrial auxiliary voltage 3 (output).	
7	Yellow	IN - COMMON	Open-terminal industrial auxiliary voltage (input) common.	
			Supported function: Whether you should connect this pin to an electrical return path or a voltage source depends on whether the third-party device is sourcing or sinking the current.	
8	Black	IN5	Open-terminal industrial auxiliary voltage 5 (input).	
9	Gray	NA	Not used	
10	Blue	IN6	Open-terminal industrial auxiliary voltage 6 (input).	
11	Violet	OUT3	Open-terminal industrial auxiliary voltage 3 (output).	
12	Gray/Pink	-VDC	Negative pole of the power provided to your device (FSR0).	 This pin must be connected to the electrical return path.
13	Red/White	OUT1	Open-terminal industrial auxiliary voltage 1 (output).	
			Supported function: see table 2 (output 2 of 3).	

The Ethernet connector is an M12 (female) 8-pin X-coded connector that provides TCP/IP communication



	Pile Number	Signal Name	Description
1	MDL_1s		Bi-directional data A+
2	MDL_1s		Bi-directional data A-
3	MDL_2s		Bi-directional data B+
4	MDL_2s		Bi-directional data B-
5	MDL_4s		Bi-directional data D+
6	MDL_4s		Bi-directional data D-
7	MDL_3s		Bi-directional data C-
8	MDL_3s		Bi-directional data C+

The Power and IO Y cable (CBL-PWR00500-M1250) transmits and receives digital IO signals and provides power to the F580 (M12-A 12-pin Male) and the Multi-Feature Integrated Light (M12-A 8-Pin Female).



Flying Leads Code (28 AMP)		Position	10 Pin & Colored Male Wire in PWB	6 Pin & Colored Female Wire in MPB
Green		OUT_COMMON	1 Green	6 Green
	Green must be connected to -VDC to operate the Multi-Feature Integrated Light.			
Brown		N/A	2 Brown	-
Yellow	OUT2		3 Yellow	-
Red	+VDC		4 Red	1 Red
Grey	IN3		5 Grey	-
White/Violet		IN_COMMON	6 White/Violet	-
Violet	IN5		7 Violet	-
White/Yellow	IN6		8 White/Yellow	-
White/Brown	IN4		9 White/Brown	-
Black	-VDC		10 Black	8 Black
Orange	PASS		7 White/Orange	-
Blue	FAIL		2 White/Blue	-
White/Green	RESERVED_PROG		3 White/Green	-