



NAPÁJECÍ ZDROJE PISA-B

Série PISA-B

PISA-B-812-B4

8-kanálová elektrická pojistka 2x1-12A, 6x1-10A
individuální alarm

- Diagnostický výstup - digitální, společný
- 8 samostatně nastavitelných kanálů
- Modely pro normu NEC CLASS2
- Šířka pouze 52 mm



POPIS PRODUKTU

PISA-B je osmikanálový ochranný modul s integrovanými elektronickými pojistkami pro 24V.

Výstupní proud pro každý kanál lze nastavit samostatně.

-B1 je vybaven společným kontaktem kontrolního relé, který indikuje spuštění všechkanálů

-B4 má výstup sériového digitálního signálu, který signalizuje blokování jednotlivých kanálů

Všechny jednotky PISA-B jsou vybaveny zásuvnýmipružinovými svorkami pro automatickou kabeláž.

Robustní pouzdro se skládá z hliníkového těla a ze zesílenéhoplastového čelního panelu, vydrží tak i okolní teploty až do + 70 °C.

SPECIFIKACE

VSTUPNÍ PARAMETRY

Vstupní napětí DC min.	19,2 V DC
Vstupní napětí DC max.	30 V DC

VÝSTUPNÍ PARAMETRY

Výstupní napětí	24 V DC
Max. výstupní proud	40 A
Výstupní proud na kanál	Channel 1-2, 1-12A, Channel 3-8, 1-10A

ROZMERY A HMOTNOST

Šířka	52 mm
Výška	124 mm
Hloubka	130 mm
Hmotnost	0,37 kg

OSTATNÍ PARAMETRY

Shoda s normami

CB, CE, cULus

Třída krytí

IP20

Svorka

Zatlačit




Fig. 6-1: CH1 and CH2 tripping diagrams in Slow mode




Fig. 6-2: CH1 and CH2 tripping diagrams in Fast mode




Fig. 6-3: CH3 to CH8 tripping diagrams in Slow mode




Fig. 6-4: CH3 to CH8 tripping diagrams in Fast mode




Fig. 7-2: LED Light pattern in measurement mode

Description:
Channel 1 is loaded with 40-60% of the set current
Channel 2 has tripped due to over current
Channel 3 is turned off on purpose (with push-button)
Channel 4 is loaded with 10-100% of the set current
Channel 5 is turned off on purpose (with push-button)
Channel 6 is loaded with 40-60% of the set current current
Channel 7 is loaded with 0-10% of the set current current
Channel 8 has tripped due to over current




Fig. 7-3: LED Light pattern in parameter mode

Description:
Channel 1 is set to 12A but turned off with push-button
Channel 2 is set to 6A but has tripped due to over current
Channel 3 is set to 6A and output is on
Channel 4 is set to 8A, but has tripped due to over current
Channel 5 is set to 2A but turned off with push-button
Channel 6 is set to 10A and output is on
Channel 7 is set to 1A and output is on
Channel 8 is set to 3A but has tripped due to over current

